

## Operation & Maintenance Instructions

Operation: Load shelves with items evenly distributed on the shelf.

Maintenance:

1. To remove dirt or grime; use a mild soap or cleanser (no abrasives). If there is any question as to suitability, test a small area on an inconspicuous part of the shelving to insure there will be no damage to the finish. Rinse to remove any residue if necessary. Do not "hose down" shelving. Dry shelving thoroughly. Do not leave liquid (or drops) on any surface.
2. Tighten all loose hardware.
3. Replace any badly worn or broken parts.



**EQ #6637, Metal Storage Cabinet  
Penco #76218A, Storage Cabinet  
36"W x 18"D x 78"H**

For LSI  
By Chris Bruce  
7/31/2009

**#5158-3M**

**InnerSpace**  
**ENGINEERING CORPORATION**  
Ph: 650/341-7700 Fax: 650/341-0244  
<http://www.InnerSpaceEng.com>

San Quentin State Penitentiary :Project  
Central Health Services Bldg. :Site  
Miscellaneous Equipment Items :Scope  
**#6637 by Penco**

## **Operation & Maintenance Instructions**

Operation: Load shelves with items evenly distributed on the shelf.

Maintenance:

1. To remove dirt or grime; use a mild soap or cleanser (no abrasives). If there is any question as to suitability, test a small area on an inconspicuous part of the shelving to insure there will be no damage to the finish. Rinse to remove any residue if necessary. Do not "hose down" shelving. Dry shelving thoroughly. Do not leave liquid (or drops) on any surface.
2. Tighten all loose hardware.
3. Replace any badly worn or broken parts.



**EQ #2485, Exchange Cart  
Eagle #ECE7S2460C, 60"W x 24"D x 72"H  
(includes all accessories shown in picture)**

For LSI  
By Chris Bruce  
7/31/2009

**#5158-4M**

**InnerSpace**  
**ENGINEERING CORPORATION**  
Ph: 650/341-7700 Fax: 650/341-0244  
<http://www.InnerSpaceEng.com>

San Quentin State Penitentiary :Project  
Central Health Services Bldg. :Site  
Miscellaneous Equipment Items :Scope  
**#2485 by Eagle Mfg.**