

Operation & Maintenance Instructions

Operation: Load shelves with items evenly distributed on the shelf.

Maintenance:

1. To remove dirt or grime; use a mild soap or cleanser (no abrasives). If there is any question as to suitability, test a small area on an inconspicuous part of the shelving to insure there will be no damage to the finish. Rinse to remove any residue if necessary. Do not "hose down" shelving. Dry shelving thoroughly. Do not leave liquid (or drops) on any surface.
2. Tighten all loose hardware.
3. Replace any badly worn or broken parts.



**EQ #6637, Metal Storage Cabinet
Penco #76218A, Storage Cabinet
36"W x 18"D x 78"H**

For LSI
By Chris Bruce
7/31/2009

#5158-3M

InnerSpace
ENGINEERING CORPORATION
Ph: 650/341-7700 Fax: 650/341-0244
<http://www.InnerSpaceEng.com>

San Quentin State Penitentiary :Project
Central Health Services Bldg. :Site
Miscellaneous Equipment Items :Scope
#6637 by Penco